

***Thank you for purchasing the Novopro SDX booth with lighting rig and bags.***




**This user manual will help you to assemble the booth safely & quickly, so please spend a few minutes to read through this assembly information.**

- It is recommended that the stand is assembled by at least 2 people.
- The corresponding parts are lettered in the image shown below.
- Due to continuous product developments, please check for the latest updated version of this product manual at: [WWW.NOVOPRO.CO.UK](http://WWW.NOVOPRO.CO.UK)

***The contents of the SDX booth are:***

- 4x Frames **A, B, C, D** from left to right.
- 2x Tubes **E**
- 2x Tubes **F**
- 2x Tubes **G**, for hanging on the lights
- 1x Tube **H**, for joining the above 2 x lighting tubes.
- 1x Tube **I** (this has 2 parts, one large and one small)
- 1x Tube **J** (this has 2 parts, one large and one small)
- 4x Cloth scrim material **K** (1 for each Individual frames)
- 2x Wooden boards **L**
- Velcro tapes and plastic feet to secure the wooden boards
- 2x Carry bags (1 large and 1 small).




### ***Start to Assemble***


- It is recommended that the stand is assembled by at least 2 people.

***Optional Scrim sets and various accessory brackets and shelves etc. are available for the SDX console: [www.novopro.co.uk](http://www.novopro.co.uk)***


1. Start by sorting the frames into A, B, C, D order.
2. Join the 4 frames A B C & D together using the hinges welded on the sides. Set frame A & D to the angle you need (frame B and C must be at 180 degrees)




3. *Insert short round tubes [I] into the larger tube [J].*
4. *Insert part I & J into section A & D as shown in the picture below.*
5. *Insert tube E on frame A and frame D as shown in the drawing below then tighten the knobs.*




*Lighting Top Bars Assembly*  
*[Lighting Gantry]*




6. *Insert tubes F into tubes E then set both tubes at the same height. Once the height has been determined, then insert the pins that into the top of tube E - it is better that you choose the height that you need now.*



7. *Add the "T" bar - tube G, onto the top of tube F and tighten the nut at the top.*



8. *Insert each end of lighting gantry joining tube H into the ends of both tubes G and tighten the bolts. If you don't want to use joining tube H you can use both G lighting bars at different heights if needed and create 2 x "T" bar setups.*



9. You can adjust the height of the lighting bars by moving up or down tubes F.
10. Adjust the angle of frame A and D then tighten the bolts under the tube I and J.  
**IMPORTANT:** You must loosen the bolts which tighten the tube H when you adjust the angle of the frames. Also there is a sign showing the max length of the tube I and J.
11. Stick the 4 scrim cloths on the rear side of the frames (the side facing the DJ), they should slightly stretch onto the frames without creasing.
12. Stick on the Velcro tapes on the tube I and J if you want to stabilize the wooden boards or affix the plastic feet to the wooden boards. **Choose the best position before fixing the feet or Velcro and bear in mind that the tubes are adjustable - but not adjustable once the boards are fixed to the tubes. PLEASE REMEMBER THIS POINT!**
13. Tighten all the screws, bolts and nuts.
14. Now you can hang on the lights and start to use your SDX booth.
15. There are two bags with this package, the bigger one is designed to hold the 4 frames (A,B,C,D), 4 cloths K and 2 wooden boards (L). The smaller bag is designed to contain all the tubes.

**Your SDX booth is now fully assembled and we are sure that this product will serve you for many years to come. Optional Scrim sets and various accessory brackets and shelves etc. are available for the SDX console: [www.novopro.co.uk](http://www.novopro.co.uk)**

There are a full range of accessories and other related products available for the SDX booth - please check out the Novopro website for more information.

***All Novopro products are thoroughly QC checked prior to dispatch but should you have any queries or questions then please contact your place of purchase or contact us at: info@novopro.co.uk***

***Novopro is a trade only supplier and only supply wholesale to trade resellers.***



For the latest updates and information on the entire Novopro range visit:

**[www.novopro.co.uk](http://www.novopro.co.uk)**

Novopro products are designed and engineered in the UK and manufactured in China.

• Email: info@novopro.co.uk • Web: www.novopro.co.uk

Due to continuous product developments & improvements, specifications and appearance are subject to change.

© Copyright Novopro Ltd 2013. E&OE.